

## TR-4000 Time & Attendance Management System



- Magnetic, Barcode, RF Card 가
- 3.5" Floppy Disk(1.44MB) Text Data , 가
- UPS Power .( 8 )
- ADP(Application Down Load Port) Update
- 4가 Event 0 ~ 99 Shift Key
- Buzzer Lock 가
- Memory Backup Battery Data 가
- LCD Battery, Memory 가
- , 가

Frequency	125KHz
Interface	3.5" Floppy Disk Driver
Memory Size	512K Bytes (11,000 )
Display	4 Function Key
	Large High-Contrast Graphic LCD
	,
	DC 12V, 500mA / Battery
	0 ~ 55
	10% ~ 90% RH
	187(W) x 148(H) x 93(D) mm

